

LIST OF MATERIALS					
ITEM	DESCRIPTION				
1	SERVICE POLE 30' MIN. CLASS 4 WOOD, CONTRACTOR PROVIDED, MODOT OWNED				
2	#2 AWG MIN. CABLE. 600 VOLT *				
3	SERVICE ENTRANCE HEAD				
4	GUY CABLE. AS REQUIRED				
5	RIGID CONDUIT. 2" MIN WITH PREFORMED ELBOWS				
6	LIGHTNING ARRESTER, VALVE TYPE, 2 POLE, 650 VOLT				
7	METER SDCKET. 200 AMP. FDR SIGNALS				
8	METER SOCKET, 200 AMP, FOR LIGHTING				
9	LOCKING, RAINTIGHT, NEMA 4 SERVICE DISCONNECT BOX				
10	INSULATED. GROUNDABLE NEUTRAL WIRE. 200 AMP MINIMUM				
11	SIGNAL BREAKERS, SINGLE POLE, 40A MIN, TYPE A OR B *				
12	LIGHTING BREAKER, 2 POLE, 240 VOLT, 100A, TYPE A OR B				
13	1/2" METAL CONDUIT				
14	#2 AWG MIN. GROUND WIRE				
15	GROUND ROD, 3/4" x 8' MIN.				
16	#8 AWG MIN. CABLE, 600 VOLT *				
17	CLASS B CONCRETE, 0.92 C.Y.±				
18	THREADED CONDUIT HUB WITH SEALING WASHERS				
19	WEATHERPROOF ADHESIVE LABEL (LIGHTING). VINYL RAISED LETTERING				
	(DR EQUIVALENT, SEE DETAIL)				
20	WEATHERPROOF ADHESIVE LABEL (SIGNALS), VINYL RAISED LETTERING				
	(DR EQUIVALENT. SEE DETAIL)				
21	W6 x 9 OR W6 x 15 GALVANIZED POST				
22	#2 AWG MIN. CABLE, 600 VOLT				
23	RIGID CONDUIT, 2" MINIMUM				
*	SEE PLANS				

## NOTES

- (A) SERVICE POLE SHALL BE GUYED WHEN SPAN OF OVERHEAD SERVICE WIRE EXCEEDS 50 FEET.
- (B) INCREASE 1 FOOT FOR EACH 5 FEET ABOVE 30 FEET.
- SERVICE DISCONNECT BOXES AND METER BOXES SHALL BE ALUMINUM OR STAINLESS STEEL. SITEL. ALL HARDWARE, HINGES, CATCHES, ETC. SHALL BE STAINLESS STEEL. METER SOXEET FOR SIGNALS OR LIGHTHING AND OTHER BOUIPMENT AND MATERIALS SHALL BE U.L. APPROVED, AND COMPORN TO THE REQUIREMENTS OF THE UTILITY COMPANY OR MUNICIPALITY PROVIDING POWER.
- O SCHEMATIC DIAGRAM SHALL BE MOUNTED ON INSIDE OF CABINET DOOR
- (E) UTILITY COMPANY SHALL DECIDE IF LIGHTNING ARRESTERS ARE TO BE CONNECTED ON THE LOAD OR LINE SIDE OF THE WETER. THE UTILITY COMPANY SHALL ASSO DECIDE IF THE LIGHTNING ARRESTER IS TERMINATED IN THE WETER OF DISCONNECT ASSOCIATION OF THE DISCONN
- LIGHTING SYSTEM VOLTAGE OF 240 VOLTS OR 480 VOLTS AS SHOWN ON THE PLANS.
- G BREAKERS SHALL CONFORM TO SEC. 901.4 OF THE STANDARD SPECIFICATIONS.
- (#) If SUBSUPFACE CONDITIONS EXIST WHICH PROPHIBIT THE PLACEMENT OF THE GROUND ROD IN A VERTICAL POSITION. THE ROD MAY BE DRIVEN AT AN OBLIQUE ANGLE NOT TO EXCEED 45 DEGREES FROM VERTICAL OR BURIED IN A TRENCH AT LEAST 30 IN. DEEP, CONNECTION TO GROUND ROD SHALL BE CADVELODE.

NERAL NOTES:

GENERAL NOTES: FOR CABLE TYPES AND INSTALLATION, SEE STANDARD SPECIFICATIONS.

THE POWER SUPPLY ASSEMBLY TYPE IS SHOWN ON THE PLANS OR IS DESIGNATED IN

THE CONTRACT. THE UTILITY COMPANY SHALL BE NOTIFIED IN WRITING 30 DAYS PRIOR TO DATE SERV

WHERE SIGNAL OR LIGHTING POWER ONLY IS DESIGNATED, OMIT ITEMS NOT REQUIRED.
ALL OPENINGS IN ANY SERVICE BOX OR METER BOX SHALL BE COVERED AND SEALED WITH

ALL MATERIALS REQUIRED AS SHOWN ON DRAWING, INCLUDING CABLE AND CONDUIT FROM POWER SUPPLY ASSEMBLY TO UTILITY COMPANY FACILITIES, SHALL BE INCLUDED IN UNIT BID PRICE FOR POWER SUPPLY ASSEMBLY.

MISSOURI HIGHWAYS AND TRANSPORTATION COMMISSION				
	HIGHWA	Y LIGHTING		
POWER SUPPLY ASSEMBLY				
	SECONDARY SERVICE			
DATE:	EFFECTIVE: 04-01-2002	901.80D	1	